

Défaillances

Poste préparation

Table motorisée

Erreur A64

Pour l'erreur du poste de travail, c'est dû à une mauvaise manipulation, ou à une descente du poste de travail contre un objet et ça a provoqué un sur couple qui désynchronisé les colonnes.

Pour remettre en opération le système il faut faire 2 opération :

- Vérifier les branchements du boîtier noir de puissance des colonnes. Ça vaut le coup après avoir mis hors tension le poste de débrancher et rebrancher tous les câbles de ce boîtier pour être sûr que tout est ok
- Quand le système a redémarré, appuyer en même temps sur montée et descente. Le poste va descendre et se mettre en butée des 2 côtés en position basse (attention il ne faut aucun obstacle sur la descente).

Si cette opération se passe bien, l'erreur A64 sera acquittée.

Borne HLP "Big 5"

Factory Reset

HOME BUTTON et POWER BUTTON au dessus du boîtier qui se trouve en haut à droite dans la borne. Il faut d'abord démonter le capot arrière de la borne.



1. Unplug power
2. Hold HOME key and reconnect power
3. Continue holding the HOME key until the unit starts Android System Recovery
4. Press HOME key to select 'wipe data/factory reset'
5. Press POWER key to select
6. (Press the HOME key until 'YES – delete all user data' is selected)
7. (Press POWER key to select)
8. After data wipe is complete, press HOME to 'reboot system now'

Revision #4

Created 21 June 2023 08:15:16 by admin_idf

Updated 19 October 2023 09:05:22 by admin_idf